

INTERMITTENT DELIVERY MODE AT HOME USING THE CADD PUMP

Patient Name: _____ **MRN** _____ **DOB** _____

Medication Information

Name of Medication : _____ Dose: _____

Medication stable at room temperature for: _____

Pump settings

Pump # : _____

Change battery every: _____ hours / days

Lock Level : _____

Reservoir volume: _____ ml

Continuous rate: _____ ml/hr

Infusion start date: _____

Pharmacist: ____/____

Pump has been programmed and double checked

Family/pharmacist will reprogram pump at home via telephone

Normal saline flush solution

Amount to give: _____ ml

When to give it:

before and after giving the medication/fluids

Heparin flush solution

Solution: _____ units/ml

Amount to give: _____ ml

When to give it:

After giving the medication and normal saline flush

Preventing Infection:

It is very important to prevent infection. Failure to do so might require removal of the central venous catheter. The nurse will show you how to keep your supplies clean, so no germs will enter the catheter and cause an infection.

Cleanliness is a must! Each time you handle supplies or perform a procedure, do the following steps:

1. Prepare a clean work space area by cleaning a solid surface with household cleanser.
2. Clean hands well, using one of the following methods:
 - Use an alcohol hand sanitizer according to directions.
 - If hands are dirty or alcohol hand sanitizer is not available, wash hands for *at least 20 seconds* with soap, rubbing all surfaces briskly, including fingernails. Use a paper towel or clean hand towel to dry your hands, and then use the towel to turn off the faucet.
3. Before *each time* you flush or attach a new syringe/tubing to the injection cap, scrub the injection cap for 30 seconds with a fresh chlorhexidine wipe, using friction. Let it dry. Do not fan or blow on it.

Getting Ready:

- 1) Make sure the medication is at room temperature
 - Remove the medication from the refrigerator as directed. Your homecare nurse will discuss with you how early this should be removed to make sure it is safe to use.
 - Do not use a microwave, oven, or water to warm.
- 2) Check the label on the bag and verify:
 - Child's name
 - Medication/Dose
 - Expiration date

Starting an infusion/medication with NEW tubing:

1. ALWAYS TURN ON the pump before attaching the tubing / cassette. To turn on the pump, remove the battery from the right side of pump, flip battery over, and replace cover.
2. The pump will go through all the settings. Be sure to verify these settings which are listed on the first page. Pump will beep multiple times when finished 'powering up'.
3. Once 'powered up', remove blue clip from tubing cassette and attach the cassette located on the tubing to the pump. Insert the 'feet' in first.
4. To latch cassette/tubing in place, use a coin and push in and turn the button located on the bottom right side of the pump, until the cassette/tubing is latched in place and the pump makes a beeping noise.
5. Screen will read "**Reset Reservoir Volume to _____ml?**" Press Y (yes) to reset the volume. (Note: this will not take place with first connection - only on following connections.)

Starting an infusion/medication WITHOUT changing the tubing (just changing the bag):

1. Stop the pump by hitting the "Stop/Start" button.
2. Press "Next" to display the "Reservoir Volume" then press Enter.
3. Screen will read "**Reset Reservoir Volume to _____ml?**" Press Y(yes) to reset volume.
OR
1. Unclamp and re-clamp cassette/tubing from pump and press Y(yes) to "**Reset Reservoir Volume to _____ml?**". You should see the message: "Resetting".

Priming the tubing (IF NOT ALREADY PRIMED):

1. Remove the cover at the end of the tubing and unclamp the tubing (keep the cover clean by placing it face up onto a clean surface).
2. When asked to "Prime Tubing?" Press the Y(yes) button. **Press N(no) if tubing is already primed.**
3. With one hand, hold the tubing with the filter (if present) end down. With your other hand, hold down the **Y(yes)** button to pump fluid through the tubing until the filter (if present) and all tubing is filled with fluid and **all air is removed**. If air bubbles are present, tap filter to remove them.
4. Clamp the tubing and replace the clean cover.

Connecting Medication/Fluids to Patient

Review of S.A.S.H. method:

1. Flush with normal **S**aline
2. **A**dminister medication or fluid
3. Flush with normal **S**aline
4. Flush with **H**eparin



Note: Every time you flush the IV line with normal saline or heparin, use the "**push-and-pause**" method: push a little solution, then pause for 1 to 2 seconds, then push a little more, pause, and so on. This method cleans the inside of the IV line. Your home care nurse will show you how to do this.

1. Gather supplies:
 - chlorhexidine wipes
 - normal saline syringes or dextrose solution syringes (2)
 - heparin syringe
 - IV medicine/fluids you will be giving
 - non-sterile gloves
 - disinfectant cap
2. Put supplies in order of use on the work surface.
3. Check the labels of the normal saline and heparin syringes, and any other medicines or fluids before giving them. Make sure they are the right medicines.
 - A medicine is good until the end of the day on the day it expires. Throw it away sooner if you see sediment in it or if you question its cleanliness. If you do throw a medicine away, be sure to call the home care pharmacy for a replacement dose.

Preparing pre-filled syringes:

All pre-filled syringes have an air bubble in them (normal saline, heparin). Remove the tip cover from the syringe and point the syringe upward, pull back slightly on plunger and squirt air bubble out.

4. Put on non-sterile gloves.
5. Remove disinfectant cap **OR** if disinfectant cap not in place, scrub the injection cap with a chlorhexidine wipe for 30 seconds and let it dry.
6. Attach normal saline syringe tip into the injection cap.
7. Unclamp the catheter.
8. Flush with normal saline using the push-and-pause method. When syringe is empty, remove it from the injection cap.
9. If you are not giving medicines at this time, go to step 1 of the next section
10. If you are giving medicines, scrub injection cap with a new chlorhexidine wipe for 30 seconds and let it dry.
11. Connect the medicine/IV tubing and give as instructed by your home care nurse.
12. Open all clamps.
13. Press the START/STOP button.
14. When “Start the Pump?” appears, press the Y (yes) button.
 - “Starting pump...” will appear on screen and pump will go through all settings once more.
 - “RUNNING” will appear on the screen, the green light will blink, and the fluid will start to flow.

At end of infusion or when medication complete:

1. Disconnect the tubing from the injection cap.
2. Scrub the injection cap with a new chlorhexidine wipe for 30 seconds and let it dry.
3. Attach normal saline syringe and flush using the push-and-pause method. When syringe is empty, remove it from the injection cap.
4. Scrub the injection cap with a new chlorhexidine wipe 30 seconds and let it dry.
5. Attach heparin syringe and flush using the push-and-pause method. When syringe is empty, remove it from the injection cap.
6. Clamp the line.
7. Apply disinfectant cap to injection cap.

Important Tips

- Make sure the pump is turned on before attaching a new cassette / tubing
- If the green light is on, the pump is running.
- If the amber light is on, the pump is *not* running.
- **The medication cassette needs to be changed at the same time every day**
 - If you hook up the medication late, it will then run that many minutes/hours late each time you hook it up for the remainder of the time the pump is being used.
For example, if it is to be hooked up at 8:00, but is not started until 9:00, then all future doses will be one hour late.
- Between changing cassettes, at least every 24 hours, the line should be flushed with 5 ml of normal saline using the push-pause method.
- Refer to the CADD Prizm instruction booklet for detailed instructions, warnings, and trouble shooting that was included in your delivery of supplies.
- To turn pump off: remove battery, flip battery over, and place back into pump.
- The pump must have a charged 9 volt battery in it to run. If the 9 volt battery dies, the pump will not run even if it is plugged into the wall or power pack.

Questions?

If you have any questions, please call your home care nurse.

Reviewed by Home Care & Home Care Pharmacy 12/2016.